Study & Analysis of Wire Rolling Process in Drawing Operation to Modify Power Transmission System

Prof. G.M. Dhote, VedangKeote¹, HarshalRaut², GauravNinawe³, Mahesh Kolte⁴, SwapnilBhutmare⁵, AishwaryTarale⁶

1,2,3,4,5,6 Bachelor Student, Department of Mechanical Engineering, Dr. Babasaseb Ambedkar College of Engineering & Research Nagpur-441110

Abstract- The aim of this project worked is to analyze and redesign a machine to upgrade it to expand its manufacturing capabilities. With the Vinavaka Industry, Nagpur being an excellent metal wire producer, this machine required redesign to meet their quality standards Their current machine set-up could not properly produce material at its largest incoming material size of 16 mm. The technical team at the Vinavaka Industry had a general idea of how they thought the machine could be upgraded. Our project group worked together with the Vinayaka Industry to gather all the details of the necessary capabilities the machine must possess. From there, We have began designing upgrades to the machine including the larger bull drum. We have used calculations to ensure these changes did not compromise any of the machine's components. We calculated the maximum draw force needed to pull the 16mm diameter wire. Using the results, calculations were completed to find the maximum torque that will be put onto the gearbox and motor of the machine. These results were then compared to the published torque curve by the manufacturer for both the gearbox and motor. With all changes implemented, the machine worked as planned and allowed the machine to roll more than 16mm diameter of wire material without surface defects from improper setup.

Index Terms- Torque, Force, Study and analysis.

INTRODUCTION

Vinayaka Group is a well-established in the manufacturing & traders of Stainless Steel Mild Steel, Carbon Steel, Alloy & Tool Steel, Die Steel & Bright Bars, Copper, Brass, Aluminium, Gun Metal, P.B. in various shapes & sizes. Vinayaka Group was incorporated in Nagpur year 1997. The Group has been scaling new heights in the market. Vinayaka

Industry has one of the drawing units with them. In the existing system, they can draw & roll the wire of a maximum 16 mm diameter. But now they want to increase the drawing capacity which may process higher diameter wires. They had tested by taking 24 mm diameter wire but during operation, they found vibrations, jerks, surface deformation & improper rolling. Therefore the company is trying to improve the existing system by modifying the current transmission system with optimum cost. Vinayaka Industry, a wire manufacturing company located in Hingna MIDC Nagpur, is in need of improving one of their wire-drawing machines. The previous machine was not designed to process the desired size of the product they would like: the Wire encounters itself, which in turn breaks down the quality of the wire and causes surface deformation. Outlining the progress We have has made since beginning this project. In this final report, we will outline the machine's previous state, and compare it to its current state.

With our newly designed methods. The machine being evaluated for this project is a wire-drawing machine, which pulls intermediate sized wire through wire-drawing dies to reduce the cross-sectional area. Typically, the machine is largest capable of producing wire from incoming diameters of 16mm (smallest) to 24mm (largest). The dies used for this process are usually made up of either polycrystalline diamond or carbide. When operating the machine, the wire is fed through a die box that contains an abrasive material and a wire die. The abrasive material is applied at the face of the die where the wire enters, which reduces the size of the wire. After the die, the wire is transferred onto a bull drum. The bull drum is what drives the motion of the wire; they

are large circular objects that are each attached to a gearbox and a motor that causes continual rotational speed.

LITERATURE REVIEW

From the literature review, we found that the machine being evaluated for this project is a wire-drawing machine, which pulls intermediately sized wires through wire-drawing dies to reduce the crosssectional area. Typically, the machine is capable of producing wire from incoming diameters of less than or equal to 16mm. The dies used for this process are usually made up of either polycrystalline diamond or carbide. When operating the machine, the wire is fed through a die box that contains a lubricant and a wire die. The lubricant is applied at the face of the die where the wire enters, which reduces the size of the wire. After the die, the wire is transferred onto a bull drum. The bull drum is what drives the motion of the wire; they are a large circular object that is attached to a gearbox and a motor that cause continual rotational speed. We were able to obtain information regarding this motor from their website. The purpose of the motor is to use to drive the gearbox, which drives the speed rate of the wire-drawing machine. On average, the motor is set to 20 hp and 1440 RPM. An idler is a slightly smaller circular object that controls the alignment of the wire around the bull drum and prevents it from encountering each other. The wire is then transferred to the cutting machine where it cut at the required length

PROPOSED METHDOLOGY

From the literature review, We have has collected for the machine's motor, gearbox, information differential, bull drum and have put forth this information into useful data calculations. From the analysis of collected data on these four machine components, we will try to find out which of these factors are critical and need to be modified or replaced by our redesign of the machine. Using this information, we can calculate the torque of the motor. as well as the average force applied. After performing design calculation we will use Ansys software to verify that our design calculations are conforming with the obtained result of the simulation. Then we will suggest these changes to be made in the wire drawing machine to the Vinayaka industry and

achieve the outputs of the experimentation that our project results in successful operation of the machine without failure.

CALCULATION

- 1) Drawing force calculation
- i) For SAE1040 without considering friction Drawing Stress (62) = Gy ((1+B)/B)[1-Ai/Ao]B Yield strength (Gy) = 415 Mpa $\mu = 0.3$ Angle of deformation (α) = 22.4160 $Ao = \pi/4 * Do2 = 201.06 mm2 = 2.01*10-4m2$ $Ai = \pi/4 * Di2 = 143013 mm2 = 1.43*10-4 m2$ $B = \mu \ Cot \ \alpha = 0.30*Cot \ (22.416) = 0.727$ 62 = 415 * ((1+0.727)/0.727)* [1-143.13/201.06]0.727 $= 215.814 \ MPa$

Drawing force (F)= 62* Ai = 215.814*143.13 = 30889.561 N

Torque required T = F*r =30889.561*0.409 =12633.830 N-m

ii) By considering Friction $GT = Gy + (G2 - Gy) e -(2\mu L)/R1$ Radius of work piece at exit (R1) = 6.75 mm Length of deformation cone (L) = 13.03 mm GT = 4165 + (215-415) e -(2*0.3*13.03)/6.75 = 352.191 MPa

Force (F) = 6T*A1= 50409.126 N

Torque (T) = F*r = 20617.332 N-m

Diam eter (Do- DI) in mm	Area (Ao -Ai) in mm2	Stress without consider ing friction in mpa	Respe ctive force in N	Stres s consi derin g fricti on in	Respect ive force in N
1		i '	1 '	mpa	
14-	153.938	245.232	25471	371.4	38577.8
11.5	-	İ '	.75	1	2

	103.868				
16-	201.06-	215.81	30889	352.1	50409.1
13.5	143.13		.56	9	3
18-	254.47-	192.65	36349	333.7	62962.2
15.5	188.69		.81	0	2
20-	314.16-	173.97	41844	316.3	76094.4
17.5	240.53		.65	6	
22-	380.132	158.56	47363	300	89594.1
19.5	-298.65		.62		
24-	452.289	145.71	52901	284.8	103422.
21.5	-363.05		.1	7	42
26-	530.93-	134.76	58451	270.9	117513.
23.5	433.74		.99	3	83

Motor torque at 1455 rpm

$$P = \frac{2 * \pi * N * T}{60}$$
$$15 * 10^3 = \frac{2 * \pi * 1450 * T}{60}$$

T = 98.78 Nm

Maximum torque generate at 2.472 rpm

$$15 * 10^3 = \frac{2*\pi*2.472*T}{60}$$

T = 57944.76 N m

For 16 mm rod

F = 50409.13

for safety assuming 20 % extra

F = 50409.13*1.2

F = 60490.956 N

Required torque at output

T = F*r

T = 60490.96*1/2

T = 30245.48 N m

 $T_{req} < T_{output}$

For 24 mm rod

F= 103422.416

F = 103422.416*1.2

F = 124106.8992 N

Required torque

T=F*r

T=124106.416*0.2

 $T_r = 51711.208$ N m

 $T_{req} < T_{output}$

From above, we can say that the motor is generating enough power to draw the 24 mm rod.

Safety calculation

1. Gear

1] Tooth Load (ft) = Pd/Vp

Design Power (Pd) = 15000 w

$$Vp = \frac{\pi * Dg * Ng}{60 * 1000}$$

= 0.095 m/s

Where,

Vp - Pitch line velocity

Dg - Diameter of gear

Ng - speed of gear

Ft = Pd/Vp

= 15000/0.075 = 200000 N

This force is transmitted by two gears so the load on

each gear equals to

Ft=200000/2= 100000

for safe condition $Fb \ge Ft$

Ft = Fb = 100000 N

Fb = So*Cv*b*y*m

Where,

Fb- Bending strength

So- Basic Strength

Velocity factor (Cv) = 3/3+Vp = 0.97

Face width of gear (b) = 110 mm

Modified Lewis factor (y) = 0.44

Module (m) =10

100000 = So*0.97*110*0.44*10

So = 213 Mpa

As So (213) < So of material of shaft i.e. En 9

(So=240) design is safe.

2] Pinion

1] Tooth Load, Ft = Pd/Vp

 $Vp = \frac{\pi * Dg * Ng}{60 * 1000}$

 $Vp = \frac{\pi * 178 * 8.654}{60 * 1000} = 0.08 \text{ m/s}$

Ft = 15000/0.08 = 187500 N

This load is transmitted by two gears Ft = 187500/2 = 93750

let Ft = Fb

93750 = So*0.97*110*0.341*10

So = 237.66 Mpa

As So (237.66) < So of material of shaft i.e En 9

(So=240) design is safe.

3] Differential

1] Tooth Load, Ft = Pd/Vp

$$Vp = \frac{\pi * Dg * Ng}{60 * 1000}$$

$$Vp = \frac{\pi * 460 * 8.654}{60 * 1000} = 0.20$$

Ft = 75000 N

75000 = So*0.93*102*0.44*7

So = 244.7 Mpa

As So (244.7) < So of material of shaft i.e SAE 1045

(So=245) design is safe.

Design calculation


4] Shaft

```
B = 16928.74 \text{ Nm}
1] Force on Shaft due to gear 1
Force = \rho * g * volume
                                                                    C = 24138.40 \text{ Nm}
Volume = \pi/4* d^2*w = 0.02463 \text{ m}^3
                                                                    D = 28963.71 Nm
                                                                    \tau = \frac{16*103}{\pi*d2} \sqrt{Kb*M + Kt*T}^2
\rho = 8055 \text{ Kg/m}^3
F = 0.02463*8055*9.81 = 1950 N
                                                                    Where.
2] Force on Shaft due to bull drum
                                                                    \tau =Shear stress
Force = g* \rho* volume
                                                                    d= diameter
\rho = 8055 \text{ Kg/ m}^3
                                                                    Kb=moment constant
Volume = 0.026 \text{ m}^3
                                                                    Kt=torque constant
Force = 0.026*9.81*8055
                                                                    T=torque
       = 2055 N
                                                                    M= Bending moment
3] Tangential Force, Ft = T/Rg
                                                                    232.5 = \frac{16*103}{7*42} \sqrt{1.75*2896322+1.5*57944^2}
Ft =104294.82 N
                                                                    d = 119.88 \text{ mm}
Where,
                                                                    = 120 \text{ mm}
T = Torque = 57944.76 \text{ N-m}
Rg = Radius of gear = 0.5 m
                                                                    21 For Shaft 2,
4] Radial Force, Fr =Ft*tanφ
                                                                    1) Reaction on gear, In Vertical
Fr =3796.21 N
                                                                    R_A + R_E = 447740 N
                                                                    \inMa = 0
5] Reactions on gear
                                                                    R_{\rm E} = \frac{31480 + 12880 + 1616}{2}
RA + RB = 214545 N
\inMa = 0
                                                                    R_E = 223870 \text{ N}
106245*0.15 + 106245*0.77 + 2055*0.12 = Rb
                                                                    Bending Moment on shaft,
*0.92
                                                                    M_A = M_E = 0
RB = 108925.43 N
                                                                    M_D = 33580.65 N-m
RA =105619.56 N
                                                                    M_C = 37920.96 N-m
Bending Moment on shaft,
                                                                    M_B = 33581.27 N-m
In Vertical plane
                                                                    2) In Horizontal
A=E=0
                                                                    R_A + R_E = 225585
B = 575.4 \text{ Nm}
                                                                    \inMa = 0
                                                                    R_{E} = \frac{11480 + 33550 + 58770}{}
D = -15455.16 Nm
C = 2055*1.05 + 106245 *0.62 - 108925.43*0.77
                                                                    R_E = 112795 \text{ N}
  = -15842.93 Nm
                                                                    Bending Moment on shaft,
In Horizontal plane
                                                                    M_A = M_E = 0
R_A + R_B = 179342.83 \ N
                                                                    M_D = 16920 \text{ N-m}
= 179343 N
                                                                    M_C = 28225 N-m
\inMa = 0
                                                                    M_B = 16920 \text{ N-m}
37960.021*0.15 + 37960.21*0.77 + 103422.41*1.2 =
                                                                    Total,
R_B* 0.92
                                                                    M_D = 37603 \text{ N-m}
R_B = 172859
                                                                    M_C = 47273 N-m
R_A = 648398
                                                                    M_B = 37605 \text{ N-m}
Bending moment on shaft,
                                                                    D^{3} = \frac{16*103}{\pi*232.5} * \sqrt{1.05*(16775)2 + 1.75*(47273)2}
A = E = 0
B = 28958.27 \text{ Nm}
C = 103422.416*1.05 + 179943*0.77 + 37360.21*
                                                                    = 112.97 \text{ mm}
0.62
                                                                    = 115 \text{ mm}
  = - 5965.249
                                                                    M = C
Resultant moment
                                                                    V^*g^*\rho = V^*g^*\rho
A=0
                                                                    \pi/4*d^2*L = \pi/4*d^2*L
```

© March 2019 | IJIRT | Volume 5 Issue 10 | ISSN: 2349-6002


L = 1246.07 mmWeight of wire (W) = V*g
Weight of wire = 10.47 Kg
Force = g*W
= 102.72 N
Speed, 74/15 = N2 / 8.65 N2 = 42.62Torque = Force / Speed 103.85/42.62 = 2.43Torque = 2.43 N-m

Project Model




Software Analysis


1. Geometry




2. Fixed Support



3. Boundary Condition, Vertical -Force 1




4. Vertical - Force 2




5. Vertical Force 3

© March 2019 | IJIRT | Volume 5 Issue 10 | ISSN: 2349-6002


6. Horizontal Force 1




7. Horizontal Force 2




8. Horizontal Force 3




9. Total Deformation




10. Equivalent Stress



11. Shear Stress



12. Max. Principal Stress





RESULT

Based on the calculations and using those values for the software analysis the following results are obtained as shown in table.

PARAMETERS	EXISTING	PROPOSED
	SYSTEM	SYSTEM
DIAMETER OF	100 M M	120 MM
MAIN SHAFT		
DIAMETER OF	85M M	110MM
2ND SHAFT		
TORQUE	30245.48 N-M	51711.208 N-M
WIRE	16-13.5 MM	24-21.5 MM
DIAMETER		


Graphical representation





From the above calculation we have seen that the current setup of wire drawing machine is generating enough power to draw 24 mm diameter rod or bar but if we draw the greater diameter bar some components may get damage. So to reduce the stresses we are increasing the diameter of shaft and providing an extra support. And From the analysis we are cross checking our work. The graph shows the relation between the diameter and stresses produced in shaft, we see that as diameter increases the stresses induced in shaft decreases.

ANALYSIS RESULT



CONCLUSIONS

From the project we can conclude that it is not feasible to draw wire of 24 mm in the present setup of drawing machine but after changing the diameter of shaft from 100mm to 120mm also the internal diameter of gears, bearings and pulleys mounted on shaft changes, providing support to it from bull drum side with no changes in power consumption. Hence our proposed design can be implemented for drawing machine of "Vinayaka Industries".

REFERENCES

- [1] Design data for machine elements by B.D. Shiwalkar.
- [2] Nguyen-Tran, H. D., Oh, H. S., Hong, S. T., Han, H. N., Cao, J., Ahn, S. H. and Chun, D. M., 2014, "A Review of Electrically-Assisted Manufacturing," J.Precis. Eng. Manuf.-Green Technol., 2(4), pp. 365–376.
- [3] Wistreich, J. G. "Ringing in Wire Drawing," Journal of the Iron and Steel Institute, Vol. 167, pp. 160–163, 1951.
- [4] Groover, M., 2010, Fundamentals of Modern Manufacture: Materials, Processes and Systems, 5th ed., Wiley, Hoboken, NJ
- [5] R. Padmanabhana, M.C. Oliveiraa, J.L. Alvesb, L.F. Menezesa, "Influence of process parameters on the deep drawing of stainless steel," Finite Elements in Analysis and Design 43 (2007) 1062

- 1067 Received 19 September 2006; Available online 23 July 2007
- [6] Anupam Agrawal, N. Venkata Reddy, P.M. Dixit, "Determination of optimum process parameters for wrinkle free products in deep drawing process," Journal of Materials Processing Technology 191 (2007) 51–54
- [7] Anupam Agrawal, N. Venkata Reddy, P. M. Dixit, "Prediction of Wrinkling and Determination of Minimum Blankholding Pressure in Multistage Deep Drawing," Journal of Manufacturing Science and Engineering, DECEMBER 2011, Vol. 133 / 061023-7
- [8] Amir Atrian, Faramarz Fereshteh-Saniee, "Deep drawing process of steel/brass laminated sheets," Composites: Part B 47 (2013)

201